



# STL Final

## SUMMARY:

As the top selling siren package, the STL Final works great with Police, Fire, and EMS vehicles.

- Powered by 12V
- Clear sound frequency
- Amplifier output power of 100-watts
- Independent siren tones for easy selection
- Siren tones include: Wail, Yelp, Sting, Siren, Horn, Tool, Hi-lo
- Includes flat brackets for mounting amplifier
- Includes microphone with 2 feet of coiled cable which extends to 6 feet
- Includes 8.5 feet of cable to speaker and power
- Includes 10 feet of cable from amp to faceplate
- Speaker sold separately
- Amplifier Dimensions: 6" L x 1.5" H x 4" D
- Faceplate Dimensions: 5" L x 3" H x 1" D
- 7 day money back guarantee
- 1 year warranty

## INSTALLATION INSTRUCTIONS:

1. The Final siren system comes with all cabling needed for installation
2. This system will include a telephone cable (one long and straight and one curly); these will connect with an adapter, also included.
3. It will also include a green male/female connector with (2) brown cables, (1) red cable, and (1) black cable.
4. Connect the phone cable to the plug in on the power supply labeled "Signal Socket".
5. Then connect the green m/f connector into the power supply to the left of the phone cable.
6. From the green m/f connector, you will wire the (2) brown cables to your speaker.
7. You will then connect the power cables from the green m/f connector, (1) red to positive and (1) black to negative, to your battery.
8. This will allow you to give power to the whole system.
9. Connect the other end of the phone cable to your face plate labeled "STL Final" and connect your microphone to your face plate.
10. Turn the unit on and power its functions using the faceplate.
11. If you order a console bracket, insert the faceplate into the bracket and screw the faceplate to the bracket using the (4) corner holes.
12. Make sure the fuse on the amplifier is secure.

